

# DCNM-FMICB Flush microphone button panel

## DICENTIS



The Microphone button panel is connected to the Flush base device (DCNM-FBD) via a control interface, and can be daisy-chained to other devices.

### Functions

- The microphone has a LED bar that indicates:
  - Red: the microphone is active.
  - Green: the participant was added to the waiting list.
  - White: it is possible to speak.

### Interconnections

- Control interface, through RJ12, to DCNM-FBD and other devices.
- Power and control interface to DCNM-FMCP.

### Parts included

Quantity	Component
1	DCNM-FMICB Flush microphone button panel

### Technical specifications

#### Mechanical

Mounting type	Click-to-fit in a metal panel with a thickness of 2 mm, or in combination with the DCN-FCOUP Flush coupling and the DCNM-FEC Flush end cap in any surrounding
Dimensions (H x W x D) (mm)	56 mm x 50 mm x 46 mm

- ▶ Also available in customized colors, wood, stone or metal designs
- ▶ Stylish and modern design
- ▶ Possible-to-speak indication available in the LED bar

Dimensions (H x W x D) (in)	2.20 in x 2 in x 1.80 in
Weight (g)	43 g
Weight (lb)	0.09 lb
Color (RAL)	RAL 9017 Traffic black

### Environmental

According to IEC 60721: storage (1K3), transportation (2K2) and operational (3K4).

Operating temperature (°C)	5 °C – 45 °C
Operating temperature (°F)	41 °F – 113 °F
Transportation temperature (°C)	-30 °C – 70 °C
Transportation temperature (°F)	-22 °F – 158 °F
Storage temperature (°C)	-5 °C – 45 °C
Storage temperature (°F)	23 °F – 113 °F
Operating relative humidity, non-condensing (%)	5% – 90%

### Ordering information

**DCNM-FMICB Flush microphone button panel**  
Flush mounted microphone button panel.  
Order number **DCNM-FMICB | F.01U.383.838**

## Services

### **EWE-DCNMFP-IW 12 mths wrty ext DICENTIS Flush Panel**

12 months warranty extension

Order number **EWE-DCNMFP-IW**

---

#### **Represented by:**

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
[www.boschsecurity.com/xc/en/contact/](http://www.boschsecurity.com/xc/en/contact/)  
[www.boschsecurity.com](http://www.boschsecurity.com)

**Germany:**  
Bosch Sicherheitssysteme GmbH  
Robert-Bosch-Platz 1  
D-70839 Gerlingen  
[www.boschsecurity.com](http://www.boschsecurity.com)

**North America:**  
Bosch Security Systems, LLC  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
[www.boschsecurity.com](http://www.boschsecurity.com)

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
[www.boschsecurity.com/xc/en/contact/](http://www.boschsecurity.com/xc/en/contact/)  
[www.boschsecurity.com](http://www.boschsecurity.com)